

System proS

3 Phase Starters, Non-Combination¹



HP Rated, Non-Reversing, 3 Phase Starters

CSA Motor Switching Current ²	Contactor Size	Maximum Motor HP ratings				Type 1	Type 4/12	Type 4X
		200/208V	220/240V	460/480V	575/600V	Catalog Number	Catalog Number	Catalog Number
9	AF09	2	2	5	7.5	PS-AFSX13	PS-AFSX43	PS-AFSXX3
17	AF16	5	5	10	15	PS-0FSX13	PS-0FSX43	PS-0FSXX3
27	AF30	10	10	20	25	PS-1FSX13	PS-1FSX43	PS-1FSXX3
52	AF52	15	20	40	50	PS-2FSX13	PS-2FSX43	PS-2FSXX3
77	AF80	25	30	60	75	PS-3FSX13	PS-3FSX43	PS-3FSXX3
125	AF140	40	50	100	125	PS-4FSX13	PS-4FSX43	PS-4FSXX3

HP Rated, Reversing, 3 Phase Starters

CSA Motor Switching Current ²	Contactor Size	Maximum Motor HP ratings				Type 1	Type 4/12	Type 4X
		200/208V	220/240V	460/480V	575/600V	Catalog Number	Catalog Number	Catalog Number
9	AF09	2	2	5	7.5	PS-AFRX13	PS-AFRX43	PS-AFRXX3
17	AF16	5	5	10	15	PS-0FRX13	PS-0FRX43	PS-0FRXX3
27	AF30	10	10	20	25	PS-1FRX13	PS-1FRX43	PS-1FRXX3
52	AF52	15	20	40	50	PS-2FRX13	PS-2FRX43	PS-2FRXX3
77	AF80	25	30	60	75	PS-3FRX13	PS-3FRX43	PS-3FRXX3
125	AF140	40	50	100	125	PS-4FRX13	PS-4FRX43	PS-4FRXX3

Coil Voltage Selection

All AC operated catalogue numbers include a 100 - 250V ac coil. To select other coil voltages, substitute the code from the coil voltage selection chart for the last digit in the catalogue number.

Ex.: A 24 - 60V ac coil is required for an AF09 starter: use PS-AFSX11

Hz	Volts			
	24 - 60	48 - 130	100 - 250	250 - 500
50/60	1	2	3	4

¹ Overload relays, pilot device kits and control transformers must be ordered separately (see pages 17 to 22)
² Ratings listed are at 600V AC