



**System PKZ 2 Motor Protectors**  
Motor Protective Trip Modules

UL / CSA / IEC / CE

Manual Motor Protectors,  
Motor Protector Combinations

UL/CSA max. 3 phase HP rating at				Adjustable thermal range (set to motor FLC)	Setting range of adjustable magnetic trips	Type	Price
200 V	230 V	460 V	575 V				
HP	HP	HP	HP	A	A	Article No.	see price list
<b>Plug-in motor protective trip modules</b>							
with overload trip  	In this range, select motor protector in accordance with the motor nameplate FLC			0,4 – 0,6	5 – 8	<b>ZM-0,6-PKZ2</b> 024232	Standard trip modules ZM-...-PKZ2 are inserted on the load side of the motor protector disconnect handle. In case of overload or short circuit, the trip module will cause the motor protector switch mechanism to open and disconnect power to the load.  Features: • Adjustable thermal and magnetic trips set in accordance with the motor FLC. • Tamper-proof lids that cover thermal and magnetic settings when the device is on. • Ambient compensation. • Phase failure sensitivity. • Coding accessory to insure insertion of correct module for the motor rating
	1/2	1/2	1	0,6 – 1	8 – 14	<b>ZM-1-PKZ2</b> 028979	
	3/4		1	1 – 1,6	14 – 22	<b>ZM-1,6-PKZ2</b> 031352	
	1/2	1/2	1	1,6 – 2,4	20 – 35	<b>ZM-2,4-PKZ2</b> 033725	
	1	1	2	2,4 – 4	35 – 55	<b>ZM-4-PKZ2</b> 036098	
	1 1/2	1 1/2	3	4 – 6	50 – 80	<b>ZM-6-PKZ2</b> 038471	
	2	3	5	6 – 10	80 – 140	<b>ZM-10-PKZ2</b> 040844	
	3	5	10	10 – 16	130 – 220	<b>ZM-16-PKZ2</b> 043217	
	7 1/2	7 1/2	20	16 – 27	200 – 350	<b>ZM-25-PKZ2</b> 045590	
	10	10	20	24 – 32	275 – 425	<b>ZM-32-PKZ2</b> 047963	
	10	15	30	32 – 42	350 – 500	<b>ZM-40-PKZ2</b> 050336	
	with overload relay function, with Hand/ Auto position  	In this range, select motor protector in accordance with the motor nameplate FLC			0,4 – 0,6	5 – 8	
1/2		1/2	1	0,6 – 1	8 – 14	<b>ZMR-1-PKZ2</b> 033950	
3/4			1	1 – 1,6	14 – 22	<b>ZMR-1,6-PKZ2</b> 033952	
1/2		1/2	1	1,6 – 2,4	20 – 35	<b>ZMR-2,4-PKZ2</b> 033955	
1		1	2	2,4 – 4	35 – 55	<b>ZMR-4-PKZ2</b> 033957	
1 1/2		1 1/2	3	4 – 6	50 – 80	<b>ZMR-6-PKZ2</b> 033966	
2		3	5	6 – 10	80 – 140	<b>ZMR-10-PKZ2</b> 033967	
3		5	10	10 – 16	130 – 220	<b>ZMR-16-PKZ2</b> 033968	
7 1/2		7 1/2	20	16 – 27	200 – 350	<b>ZMR-25-PKZ2</b> 033969	
10		10	20	24 – 32	275 – 425	<b>ZMR-32-PKZ2</b> 033973	
10		15	30	32 – 42	350 – 500	<b>ZMR-40-PKZ2</b> 033975	