preset dimmers



- slider button turns lights
 on/off
- slide up to brighten, down to dim
- large control measures
 4.56" x 4.56" (fits into a
 1-gang backbox)
- small control shown

incandescent/halogen (small control)

single pole/3-way	600 W	N-603P-		
single pole/3-way	1000 W	N-1003P-		
incandescent/halogen (large control)				
single pole/3-way	1500 W	N-1503P-		
single pole/3-way	2000 W	N-2003P-		

magnetic low-voltage (small control)

magnetie ien re		ornalon		
single pole/3-way	600 VA	NLV-603P-		
	(450 W)			
single pole/3-way	1000 VA	NLV-1003P-		
	(800W)			
magnetic low-voltage (large control)				
single pole/3-way	1500 VA	NLV-1503P-		
	(1200W)			
single pole/3-way	2000 VA	NLV-2003P-		
	(1600W)			

Suggested maximum lighting load for magnetic low-voltage dimming is 450W for 600VA products, 800W for 1000VA products, 1200W for 1500VA, and 1600W for 2000VA to allow for transformer losses.

For 3-way and 4-way switching use N-3PS-, N-4PS- or other mechanical switches.

linear-slide switches




- slide up to on, down to off
- use with any 20 A load
- general purpose switching of all sources and motor loads
- for 347 V products insert color suffix before "CSA" in model number
- no derating if ganged

general purpose switches

3				
single po	le 120V/277V	20 A	N-1PS-	
single po	le 347 V	20 A	N-1PS-347-	-CSA
3-way	120V/277V	20 A	N-3PS-	
3-way	347 V	20 A	N-3PS-347-	-CSA
4-way	120V/277V	20 A	N-4PS-	

slide-to-off fan controls



- slide up to on/increase speed, down to decrease/off
- large control measures 4.56" x 4.56" (fits into a 1-gang backbox)
- small control shown
- for use with multiple ceiling paddle fans or exhaust fans
- no derating if ganged

fully variable control (small control)

single pole	6A	NFS-6E-		
fully variable control (large control)				
single pole	12A	NFS-12E-		

See page 33 for available colors. To order, add color suffix to model number. Example: N-603P- WH 2.75" (70mm)



Shown actual size: Nova® dimmer in white (WH) (includes wallplate)



product family features

- visible heat sink (see page 46)
- slide adjusts light to suit any activity
- full family of controls plus matching fan controls, switches and wiring devices
- dimmer includes 1-gang wallplate
- use "no fins broken" wallplates for full wattage capacity in multi-gang applications
- does not mount with Nova T☆_® under common wallplate
- voltage compensation maintains stable light levels despite line voltage variations

Questions on installation or selection? Call Lutron_® 24 hours/7 days a week at 1.800.523.9466 or visit www.lutron.com

available models

source type

- ♀ incandescent/halogen lighting
- $\overline{\mathbb{V}}$ magnetic low-voltage lighting
- ₩ electronic low-voltage lighting
- ____ neon/cold cathode
- *Z*☞ fluorescent lighting
- LED lighting
- 🖗 fully variable fan controls

control locations

■ single pole (one location)
 ■ 0 3-way (two locations)

available colors (see page 14 for color swatches)

colors (matte finish)

WH	white	GR	gray
BE	beige	TP	taupe
IV	ivory	BR	brown
AL	almond	BL	black
LA	light almond	SI	sienna

CAD file downloads available at www.lutron.com/cad

Multi-gang, screwless, seamless wallplates available – wallplate selector tool at www.lutron.com/lutron/wallplate