Wallplates for Abella®, Ceana®, Ariadni®, **Glyder**[®] and Rotary





1-gang	FG-1- <u>CC</u> 3	3-gang	FG-3- <u>CC</u> 3
Stainless Steel*	FW-1-SS	Stainless Steel*	FW-3-SS
W: 2.86 in (73 mm); H: 4.60 in (117 mm);		W: 6.48 in (165 mm); H: 4.60 in (117 mm);	
D: .23 in (5.8 mm)		D: .23 in (5.8 mm)	



2-gang	FG-2- CC 3
Stainless Steel*	FW-2-SS
W: 4.67 in (119 mm); H: 4.60 in (117 mm);	
D: .23in (5.8mm)	

Combination opening



Rotate the wallplate for small/large or large/small opening applications.

FG-2-TD-CC3

2-gang (1 traditional, 1 designer opening) Stainless Steel* FW-2-TD-SS W: 4.67 in (119 mm); H: 4.60 in (117 mm); D: .23 in (5.8 mm)

CC³: Gloss color codes, see pg. 167

Multiple devices with line and low-voltage can be mounted behind a common wallplate using a standard barrier backbox, see Application Note #213 (Combining Low-Voltage and Line Voltage Wiring Devices in a Multi-Gang Box) at

www.lutron.com/applicationnotes.

Controls must have heat-sink fins broken for multi-gang installations. Removing this metal reduces the amount of heat that the control can dissipate, thus reducing the wattage capacity of the control. Please derate dimmers and switches as required.

Multi-gang dimmer installations may require derating, see pg. 170.

Controls must have heat-sink fins broken for multi-gang installations. Multi-gang dimmer installations may require derating, see pg. 170.

*Stainless Steel wallplates include black plastic trim/adapter, visible from side. Match with separate Black (BL) controls.