

Fan and fan/light control model numbers

 **Fan controls**

Digital fan control—quiet 7-speed

Multi-location/single-pole MIR-FQ4FM-**CC**¹
120V up to 4 canopy modules (1 A each)

Multi-location/single-pole MIR-FQ4FMT-**CC**¹
fan package
120V up to 4 canopy modules (1 A each)

All above include one wall-mounted fan control and one fan-mounted canopy module. Wallplates sold separately.

MIR-FQ4FMT- model includes IR remote control.

No derating required if ganged.

Models may be used with up to two companion fan/light controls (MA-ALFQ35-).

 **Fan/light controls**

Fan/light control—quiet 7-speed

Single-pole MIR-LFQTHW-**CC**¹
120V 300W light (top)
1 canopy module for up to 1 A fan (bottom)

Multi-location MIR-LFQMT-**CC**¹
120V 300W light (top)
1 canopy module for up to 1 A fan (bottom)

All above include one wall-mounted fan/light control, one fan-mounted canopy module and one IR remote control.

Wallplates sold separately.

No derating required if ganged.

MIR-LFQTHW- model includes wallplate.

Multi-location model may be used with up to two companion fan/light controls (MA-ALFQ35-).

Canopy module (fan mounted)

Canopy module CM-FQ1
120V 1 A

CC¹: Gloss and Satin color codes, see pg. 61

CC³: Gloss color codes, see pg. 61

CC⁴: Satin color codes, see pg. 61

(Wallplates not included with above, order separately, see pg. 160)

Companion dimmer, fan, fan/light and IR control model numbers

Companion controls

Companion dimmer

Companion dimmer MA-R-**CC**³
120V

Companion dimmer MSC-AD-**CC**⁴
120V

No derating required if ganged.

Companion fan control

Companion fan control MA-AFQ4-**CC**¹
120V

Use up to a maximum of two wall-mounted companion fan controls (MIR-FQ4FMT- or MIR-FQ4FM-) for multi-location control.

No derating required if ganged.

Companion fan/light control

Companion fan/light control MA-ALFQ35-**CC**¹

No derating required if ganged.

IR remote controls

IR remote control MIR-ITFS-WH
(light only)

IR remote control MIR-ITFS-F-WH
(fan only)

IR remote control MIR-ITFS-LF-WH
(fan/light)

Must be within 30 ft line-of-sight to IR receiver.

All models must be derated if ganged unless otherwise noted, see pg. 170.