



Energy Saver T2

EL/mdTQS 13W T2

The Philips EnergySaver T2 provides energy efficient lighting in a smaller, sleeker, size that fits more fixtures. The energy saving T2 is a direct replacement for most incandescents, provides soft white light and lasts 11 years* reducing the hassle of frequest replacements.

Product data


General Information	
Cap-Base	E26 [Single Contact Medium Screw]
Bulb Shape	EL/mdTQS
Nominal Lifetime (Nom)	10000 h
Switching Cycle	5000X
Light Technical	
Color Code	827 [CCT of 2700K]
Initial lumen (Nom)	900 lm
Luminous Flux (Rated) (Nom)	900 lm
Color Designation	Warm White (WW)
Lumen Maintenance 2000 h (Nom)	85 %
Lumen Maintenance 5000 h (Nom)	70 %
Chromaticity Coordinate X (Nom)	459
Chromaticity Coordinate Y (Nom)	412
Correlated Color Temperature (Nom)	2700 K
Luminous Efficacy (rated) (Nom)	67 lm/W
Color Rendering Index (Nom)	81
LLMF At End Of Nominal Lifetime (Nom)	50 %
Operating and Electrical	
Input Frequency	50 or 60 Hz

Power (Rated) (Nom)	13.0 W
Lamp Current (Nom)	210 mA
Wattage Equivalent	60 W
Warm Up Time To 60% Light (Min)	5 s
Warm Up Time To 60% Light (Max)	40 s
Power Factor (Nom)	0.55
Voltage (Nom)	110-127 V
Controls and Dimming	
Dimmable	No
Approval and Application	
Energy Efficiency Label (EEL)	A
Mercury (Hg) Content (Max)	2 mg
Energy Consumption kWh/1000 h	13 kWh
Product Data	
Order product name	EL/mdTQ 13W T2
EAN/UPC - Product	046677413996
Order code	413996
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6

Energy Saver T2

Material Nr. (12NC)	929689749502
Net Weight (Piece)	0.056 kg

Dimensional drawing



EL/mdTQ 13W T2 51.5 mm 104.3 mm 42.5 mm

с

F

D

TORNADO T2 13W/827 E26 110-127V 50/60Hz



Product

© 2016 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.

www.lighting.philips.com 2016, November 9 - data subject to change