

PERFORMANCE DATA

Allowable Load Capacities for Zip-It in Wallboard¹

Anchor	3/8" Wallboard		1/2" Wallboard		5/8" Wallboard		3/4" Wallboard	
	Tension lbs. (kN)	Shear lbs. (kN)	Tension lbs. (kN)	Shear lbs. (kN)	Tension lbs. (kN)	Shear lbs. (kN)	Tension lbs. (kN)	Shear lbs. (kN)
Zip-It	15 (0.1)	15 (0.1)	15 (0.1)	20 (0.1)	20 (0.1)	25 (0.1)	20 (0.1)	25 (0.1)
Zip-It Jr.	10 (0.0)	15 (0.1)	15 (0.1)	15 (0.1)	20 (0.1)	20 (0.1)	20 (0.1)	20 (0.1)

1. Allowable load capacities listed are calculated using an applied safety factor of 4.0.

ORDERING INFORMATION

Nylon Zip-It

Cat. No.	Wall Thickness	Description	Std. Box	Std. Carton	Wt./100
2345	3/8" to 1"	Std. Box (No screws)	100	1,000	1/2
2348	3/8" to 1"	Std. Box, No. 8 x 1" screws	100	1,000	1 1/4
2355	3/8" to 1"	Master Carton (No screws)	–	5,000	1/2

Zinc Zip-It

Cat. No.	Wall Thickness	Description	Std. Box	Std. Carton	Wt./100
2346	3/8" to 1"	Std. Box (No screws)	100	1,000	2
2349	3/8" to 1"	Std. Box, No. 8 x 1" screws	100	1,000	2 1/2
2356	3/8" to 1"	Master Carton (No screws)	–	5,000	1 3/4

Core Zip-It

Cat. No.	Wall Thickness	Description	Std. Box	Std. Carton	Wt./100
2370	3/8" to 1"	Nylon Core Zip-It	100	1,000	1/2
2371	3/8" to 1"	Zinc Core Zip-It	100	1,000	1 1/4
2390	3/8" to 5/8"	Nylon Core Jr. Zip-It	100	1,000	1/4

Core Zip-It available only in Canada.

Zip-It Kits

Cat. No.	Material	Description	Std. Box	Std. Carton	Wt./100
2368	Nylon	50 Anchors, No. 8 x 1" Screws, & No. 2 Phillips Driver Bit	1	10	7
2369	Zinc	50 Anchors, No. 8 x 1" Screws, & No. 2 Phillips Driver Bit	1	10	13 1/4

Nylon Zip-It Jr.

Cat. No.	Wall Thickness	Description	Std. Box	Std. Carton	Wt./100
2350	3/8" to 5/8"	Std. Box (No screws)	100	1,000	1/4
2351	3/8" to 5/8"	Std. Box, No.6 x 1" screws	100	1,000	3/4

Zinc Zip-It Jr.

Cat. No.	Wall Thickness	Description	Std. Box	Std. Carton	Wt./100
2362	3/8" to 5/8"	Std. Box (No screws)	100	1,000	1
2364	3/8" to 5/8"	Std. Box, No.6 x 1" screws	100	1,000	3
2363	3/8" to 5/8"	Master Carton (No screws)	–	5,000	1

Zip-It Jr. Kits

Cat. No.	Material	Description	Std. Box	Std. Carton	Wt./100
2367	Nylon	50 Anchors, No. 6 x 1" Screws, & No. 2 Phillips Driver Bit	1	10	7
2361	Zinc	50 Anchors, No. 6 x 1" Screws, & No. 2 Phillips Driver Bit	1	10	13 1/4

Note: To select the proper screw length required, determine the thickness of the fixture, including any spacers or shims and add 3/4".

© 2006 Powers Fasteners, Inc. All Rights Reserved. Zip-It is a registered trademark of Powers Fasteners, Inc.

