













4" LINE VOLTAGE SQUARE TRIM SERIES DOWNLIGHT, PINHOLE, ADJUSTABLE, LENSED

Project: _____

Fixture Type: _____

Location: _____

Contact/Phone: _____

Trim Series	Dimensions	Aperture	Catalog No.	Housing/Lamp Compatibility
 Square Downlight	 5"	 2-5/32"	17SQ-HZ-WH - Haze, White Trim 17SQ-W-WH - White, White Trim 17SQ-B-WH - Black, White Trim 17SQ-WHZ-WH - Wheat Haze, White Trim Not Wet Location approved when used with LED housings	IC1/IC1W/IC1S: 50W PAR20 (Requires T599 socket extender), 39W PAR20, 30W R20 IC1P/TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series
 Square Pinhole	 5"	1-1/4"	13SQ-WH - White Trim	IC1/IC1W/IC1S: 39W PAR20 (Requires T599 socket extender), 35W PAR20, 30W R20 IC1P: 50W PAR20, 30W R20 TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series
 Square Flush Gimbal	 5" Adjustment: 35° Vertical		440SQ-WH - White Trim 440SQ-BL - Black Trim	IC1/IC1W/IC1S: 35W MR16 120V GU10 Base IC1P/TC1/TC1S/TC1R: 50W MR16 120V GU10 Base All of the above requires Juno part# GU10-WHIP
 Square Frosted Lens with Clear Center	 5"		12SQ-W-WH - Perimeter Frosted Lens, White Trim	IC1/IC1W/IC1S: 50W PAR20 (Requires T599 socket extender), 30W R20 IC1P/TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series

