

# Pilot and Signaling Devices

## Heavy-Duty 22.5 mm Watertight/Oiltight Selector Switches

### C-2000

## Section 9

### 3-Position Knob Operated Selector Switches

Non-Illuminated

600 VAC Max., 300 VDC Max.

10 Amps Continuous AC, 2.5 Amps Continuous DC

#### Selection Process

Select operator below + Select contact block(s) from page 9-93 + Select nameplate, if required, from pages 9-95 to 9-97 = Complete Unit



#### Knob 3-Position

Position Type	Operator Style	Release Type	Cam Codes	Product Number	GO-10GC
3-Position	Round Polished Chrome	Maintained	Z, E, L, U	P9CSM†0*	
3-Position	Round Satin Chrome	Maintained	Z, E, L, U	P9MSM†0*	
3-Position	Round Engineered Plastic	Maintained	Z, E, L, U	P9XSM†0*	
3-Position	Square Engineered Plastic	Maintained	Z, E, L, U	P9SSM†0*	
3-Position	Round Polished Chrome	Spring Return L → C	Z, E, L, U	P9CSM†1*	
3-Position	Round Satin Chrome	Spring Return L → C	Z, E, L, U	P9MSM†1*	
3-Position	Round Engineered Plastic	Spring Return L → C	Z, E, L, U	P9XSM†1*	
3-Position	Square Engineered Plastic	Spring Return L → C	Z, E, L, U	P9SSM†1*	
3-Position	Round Polished Chrome	Spring Return C ← R	Z, E, L, U	P9CSM†5*	
3-Position	Round Satin Chrome	Spring Return C ← R	Z, E, L, U	P9MSM†5*	
3-Position	Round Engineered Plastic	Spring Return C ← R	Z, E, L, U	P9XSM†5*	
3-Position	Square Engineered Plastic	Spring Return C ← R	Z, E, L, U	P9SSM†5*	
3-Position	Round Polished Chrome	Spring Return L → C ← R	Z, E, L, U	P9CSM†3*	
3-Position	Round Satin Chrome	Spring Return L → C ← R	Z, E, L, U	P9MSM†3*	
3-Position	Round Engineered Plastic	Spring Return L → C ← R	Z, E, L, U	P9XSM†3*	
3-Position	Square Engineered Plastic	Spring Return L → C ← R	Z, E, L, U	P9SSM†3*	


3-Position Selector Switches

Replace double dagger (‡) in product number with cam code from cams table below.


#### Cams

Choose desired cam. Note selection and position of contact block(s).

‡Cam Code				Screw Terminal Contact Block		Quick-Connect Terminal Contact Block	
				Position 1	Position 2	Position 1	Position 2
Z	0	0	X	P9B10VN	—	P9B10FN	—
	X	0	0	—	P9B10VN	—	P9B10FN
	X	X	0	P9B01VN	—	P9B01FN	—
	0	X	X	—	P9B01VN	—	P9B01FN
	0	0	X	P9B11VN	—	—	—
	X	X	0	—	—	—	—
	0	X	X	—	P9B11VN	—	—
E	0	0	X	—	P9B01VN	—	P9B01FN
	0	X	0	P9B10VN	—	P9B10FN	—
	0	0	X	P9B11VN	—	—	—
	0	0	X	P9B11VN	—	—	—
L	X	0	0	—	P9B10VN	—	P9B10FN
	0	X	0	P9B01VN	—	P9B01FN	—
	X	0	0	P9B11VN	—	—	—
	0	X	0	—	—	—	—
U	0	0	X	P9B11VN	—	—	—
	0	X	0	—	—	—	—
	0	0	X	—	P9B11VN	—	—
	X	0	0	—	P9B11VN	—	—



Operator Positions



Contact Block Positions (viewed from rear)

Replace asterisk (\*) in product number with color code from colors table below.

#### \*Colors

Colors	Black	Red	Green	Yellow	Blue	No Knob <sup>1</sup>
*Color code	N	R	V	G	L	0

