



REPEATER & AWAY EMULATOR, BLACK

MRR2-G | [On-Q](#)

FEATURES & BENEFITS

USAGE

The Repeat and Away Emulator records the normal usage of lights throughout the home and plays them back while homeowners are away. It also extends the range between the controller (LC7001) and a connected device by 100 ft. per repeater. Up to two repeaters are supported for a maximum coverage distance of 300 ft.

Check out the [RF Lighting Control mobile app](#).

- Patented 900 MHz RF communication protocol avoids interference with other 900 MHz devices, such as cordless phones and baby monitors
- Simulates occupancy to deter potential break-ins
- Extends the range between the controller (LC7001) and a connected device by 100 ft. per repeater
- Up to two repeaters can be installed on a single system
- No network wiring is necessary
- Compatible with the radiant® RF Lighting Control and adorne® Wi-Fi Ready lighting control devices

SPECIFICATIONS

GENERAL INFO

Color: Black

Type: Accessories

LISTING AGENCIES/THIRD PARTY CERTIFICATIONS

CSA Listing Info: CAN/CSA-C22.2 No. 14- 2005

CSA Standard: Yes

FCC Standard: Yes

UL Listing No: UL 244A

UL Standard: Yes

UN SPSC: 39121107

DIMENSIONS

Depth (Metric): 2.5 cm

Depth (US): 1"

Length (Metric): 9.4 cm

Length (US): 3.69 in

Width (Metric): 9.5 cm

Width (US): 3.75 in

TECHNICAL INFORMATION

Compatible Power Supplies: Included

Frequency: 900MHz, Patented Top Dog™ Frequency-agile RF Wireless

Humidity: 0-95% RH, non-condensing

mA: 50mA

Mounting: Screw slot for wall mounting, rubber feet for shelf-top mounting

Operating Temperature (Celsius): 0°C to 40°C

Power Requirements: 9-12VDC, 50mA minimum

Volts (DC): 9-12VDC