
PIR WALL SWITCH VACANCY SENSOR

CS-50 | [Wattstopper](#)



FEATURES & BENEFITS

The CS-50 Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications in the home. It is engineered to comply with California's Title 24-2013 residential energy code.

- Automatic-off control
- Two-wire sensor; no neutral connection
- LED status indicator
- Adjustable time delay
- Compliant with California Title 24-2008

SPECIFICATIONS

MODELS

Product Number: CS-50-W, CS-50-I, CS-50-LA, CS-50-A, CS-50-B

GENERAL INFO

Typical Applications: Bedroom, Family/Living Room

Type: Incandescent,LED,Fluorescent, CFL, Magnetic Low Voltage,Electronic Low Voltage,1/6 hp motor

Special Features: CA Title 24-2008 Compliant

TECHNICAL INFORMATION

IR Range On Axis: 180 degrees, 600 sq ft

LightOutput 1FCD: Manual On

Load: 0-600W

Response Time: Adjustable

Volts: 120VAC,60Hz