# S201-C2



Products + Low Voltage Products and Systems + Modular DIN Rail Products + Miniature Circuit Breakers MCBs

Parts & Services + Drives + Medium voltage AC drives + Special purpose drives + ACS1000

Parts & Services + Drives + Medium voltage AC drives + Special purpose drives + ACS5000

Parts & Services + Robotics + Controllers + IRC5 + IRC5 Single

#### General Information

Extended Product Type: S201-C2

**Product ID:** 2CDS251001R0024 **EAN:** 4016779523325

Catalog Description: Miniature Circuit Breaker - S200 - 1P - C - 2 ampere

Long Description: System pro M compact S200 miniature circuit breakers are current limiting.

They have two different tripping mechanisms, the delayed thermal tripping mechanism for overload protection and the electromechanic tripping mechanism for short circuit protection. They are available in different characteris tics (B,C,D,K,Z), configurations (1P,1P+N,2P,3P,3P+N,4P), breaking capacities (up to 6 kA at 230/400 V AC) and rated currents (up to 63A). All MCBs of the product range S200 comply with IEC/EN 60898-1, IEC/EN 60947-2, UL1077 and CSA 22.2 No. 235, allowing the use for residential, commercial and industrial applications. Bottom-fitting auxiliary contact can be mounted

d on S200 to save 50% space.

#### Ordering

Minimum Order Quantity: 1 piece

Customs Tariff Number: 85362010

Popular Downloads

Data Sheet, Technical Information: 2CDC002157D0102

Instructions and Manuals: 2CSC400002D0208

**Dimensions** 

Product Net Width: 17.5 mm

Product Net Depth: 69 mm

Product Net Height: 88 mm

Product Net Weight: 0.125 kg

Technical

Standards: IEC/EN 60898-1

IEC/EN 60947-2

UL 1077

1

Number of Poles:

| Tripping Characteristic:   | С   |
|--|---|
| Rated Current (I <sub>n</sub> ):                                   | 2 A   |
| Rated Operational Voltage:   | acc. to IEC 60898-1 230 / 400 V AC<br>acc. to IEC 60947-2 230 V AC  |
| Power Loss:  | 1.8 W<br>at Rated Operating Conditions per Pole 1.8 W   |
| Rated Insulation Voltage (U <sub>i</sub> ):                        | acc. to IEC/EN 60664-1 440 V  |
| Operational Voltage:   | Maximum (Incl. Tolerance) 253 V AC Maximum (Incl. Tolerance) 72 V DC Maximum 253 V AC Maximum 72 V DC Minimum 12 V AC Minimum 12 V DC |
| Rated Frequency (f):   | 50 Hz<br>60 Hz  |
| Rated Short-Circuit Capacity (I <sub>cn</sub> ):                   | (230 / 400 V AC) 6 kA   |
| Rated Ultimate Short-Circuit Breaking Capacity (I <sub>cu</sub> ): | (133 V AC) 20 kA<br>(230 V AC) 10 kA  |
| Rated Service Short-Circuit Breaking Capacity (I <sub>cs</sub> ):  | (133 V AC) 15 kA  |
| Energy Limiting Class:   | 3   |
| Overvoltage Category:  | III   |
| Pollution Degree:  | 3   |
| Rated Impulse Withstand Voltage $(U_{imp})$ :                      | 4 kV<br>(6.2 kV @ sea level)<br>(5.0 kV @ 2000 m)   |
| Dielectric Test Voltage:   | 50 / 60 Hz, 1 min: 2 kV   |
| Housing Material:  | Insulation Group II, RAL 7035   |
| Actuator Type:   | Insulation group II, black, sealable  |
| Contact Position Indication:                                       | Red ON / Green OFF  |
| Degree of Protection:  | IP20  |
| Remarks:   | IP40 in enclosure with cover  |
| Electrical Endurance:  | 20000 AC cycle  |
| Mechanical Endurance (N <sub>endu</sub> ):                         | 20000 cycle   |
| Terminal Type:   | Screw Terminals   |
| Screw Terminal Type:   | Failsafe Bi-directional Cylinder-lift Terminal  |
| Connecting Capacity:   | Busbar 10 / 10 mm² Flexible with Ferrule 0.75 25 mm² Flexible 0.75 25 mm² Rigid 0.75 35 mm² Stranded 0.75 35 mm²                      |
| Tightening Torque:   | 2.8 N·m   |

| Recommended Screw Driver:  | Pozidriv 2  |
|--|---|
| Mounting on DIN Rail:  | TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715 |
| Mounting Position:   | Any   |
| nvironmental   |   |
| Ambient Air Temperature:   | Operation -25 +55 °C<br>Storage -40 +70 °C  |
| Resistance to Shock acc. to IEC 60068-2-27:  | 25g / 2 shocks / 13 ms  |
| Resistance to Vibrations acc. to IEC 60068-2-6:  | 5g, 20 cycles at 5 150 5 Hz with load 0.8 In  |
| Environmental Conditions:  | 28 cycles<br>with 55 °C / 90-96 %<br>and 25 °C / 95-100 %   |
| RoHS Status:   | Following EU Directive 2002/95/EC August 18, 2005 and amendment   |
| echnical UL/CSA  |   |
| Maximum Operating Voltage UL/CSA:  | 60 V DC<br>480Y/277 V AC  |
| Connecting Capacity UL/CSA:  | Busbar 18-8 AWG<br>Conductor 18-4 AWG   |
| Tightening Torque UL/CSA:  | 25 in·lb  |
| Interrupting Rating acc. to UL1077:  | (133 V AC) 6 kA<br>(277 V AC) 6 kA<br>(480Y / 277 V AC) 6 kA<br>(60 V DC) 10 kA                             |
| ertificates and Declarations (   | Document Number)  |
| Declaration of Conformity - CE:  | 2CDK403001D0604   |
| Environmental Information:   | 2CDK400030D0201   |
| Instructions and Manuals:  | 2CSC400002D0208   |
|  |   |
| RoHS Information:  | 2CDK400003K0201   |
|  | 2CDK400003K0201   |
| RoHS Information:  | 2CDK400003K0201  10 piece   |
| RoHS Information: ontainer Information   |   |
| RoHS Information:  Ontainer Information  Package Level 1 Units:  | 10 piece  |
| RoHS Information: Ontainer Information Package Level 1 Units: Package Level 1 Width:                         | 10 piece<br>92 mm   |
| RoHS Information: Ontainer Information Package Level 1 Units: Package Level 1 Width: Package Level 1 Length: | 10 piece<br>92 mm<br>183 mm   |

120 piece

Package Level 2 Units:

| Package Level 2 Width:        | 275 mm        |
|-------------------------------|---------------|
| Package Level 2 Length:       | 395 mm        |
| Package Level 2 Height:       | 210 mm        |
| Package Level 2 Gross Weight: | 14.8 kg       |
| Package Level 2 EAN:          | 4016779970518 |

## Classifications

| Object Classification Code: | F  |
|-----------------------------|--|
| E-nummer:                   | 2100504                                    |
| ETIM 4:                     | EC000042 - Miniature circuit breaker (MCB) |
| ETIM 5:                     | EC000042 - Miniature circuit breaker (MCB) |
| ETIM 6:                     | EC000042 - Miniature circuit breaker (MCB) |
| ETIM 7:                     | EC000042 - Miniature circuit breaker (MCB) |
| eClass:                     | 7.0 27141901                               |
| UNSPSC:                     | 39121614                                   |

### Accessories

| Identifier      | Description                            | Туре       | Qty | Unit Of Measure |
|-----------------|--|------------|-----|-----------------|
| 2CCA880100R0001 | CMS-100PS Sensor                       | CMS-100PS  | 1   | piece           |
| 2CCA880101R0001 | CMS-101PS Sensor                       | CMS-101PS  | 1   | piece           |
| 2CCA880102R0001 | CMS-102PS Sensor                       | CMS-102PS  | 1   | piece           |
| 2CDS200909R0001 | S2C-A1 - Shunt Trip                    | S2C-A1     | 1   | piece           |
| 2CDS200909R0002 | S2C-A2 - Shunt Trip                    | S2C-A2     | 1   | piece           |
| 2CDS200912R0001 | S2C-H6R - Auxiliary Contact            | S2C-H6R    | 1   | piece           |
| 2CDS200918R0001 | S2C-NT - Hand Operated Neutral         | S2C-NT     | 1   | piece           |
| 2CDS200922R0001 | S2C-S/H6R - Signal / Auxiliary Contact | S2C-S/H6R  | 1   | piece           |
| 2CDS200936R0001 | S2C-H11L - Auxiliary Contact           | S2C-H11L   | 1   | piece           |
| 2CDS200936R0002 | S2C-H20L - Auxiliary Contact           | S2C-H20L   | 1   | piece           |
| 2CDS200936R0003 | S2C-H02L - Auxiliary Contact           | S2C-H02L   | 1   | piece           |
| 2CDS200946R0001 | S2C-H6-11R - Auxiliary Contact         | S2C-H6-11R | 1   | piece           |
| 2CDS200946R0002 | S2C-H6-20R - Auxiliary Contact         | S2C-H6-20R | 1   | piece           |
| 2CDS200946R0003 | S2C-H6-02R - Auxiliary Contact         | S2C-H6-02R | 1   | piece           |
|                 |  |            |     |                 |

| ldentifier      | Description                          | Туре          | Qty | Unit Of Measure |
|-----------------|--------------------------------------|---------------|-----|-----------------|
| 2CDS200970R0001 | S2C-H01 - Auxiliary Contact          | S2C-H01       | 1   | piece           |
| 2CDS200970R0002 | S2C-H10 - Auxiliary Contact          | S2C-H10       | 1   | piece           |
| 2CSS200911R0001 | S2C-UA 12 DC - Undervoltage release  | S2C-UA 12 DC  | 1   | piece           |
| 2CSS200911R0002 | S2C-UA 24 AC - Undervoltage release  | S2C-UA 24 AC  | 1   | piece           |
| 2CSS200911R0003 | S2C-UA 48 AC - Undervoltage release  | S2C-UA 48 AC  | 1   | piece           |
| 2CSS200911R0004 | S2C-UA 110 AC - Undervoltage release | S2C-UA 110 AC | 1   | piece           |
| 2CSS200911R0005 | S2C-UA 230 AC - Undervoltage release | S2C-UA 230 AC | 1   | piece           |
| 2CSS200911R0006 | S2C-UA 400 AC - Undervoltage release | S2C-UA 400 AC | 1   | piece           |
| 2CSS200911R0007 | S2C-UA 24 DC - Undervoltage release  | S2C-UA 24 DC  | 1   | piece           |
| 2CSS200911R0008 | S2C-UA 48 DC - Undervoltage release  | S2C-UA 48 DC  | 1   | piece           |
| 2CSS200911R0009 | S2C-UA 110 DC - Undervoltage release | S2C-UA 110 DC | 1   | piece           |
| 2CSS200911R0010 | S2C-UA 230 DC - Undervoltage release | S2C-UA 230 DC | 1   | piece           |
| 2CSS200998R0001 | S2C-BP - Mechanical tripping device  | S2C-BP        | 1   | piece           |
| 2CSS200999R0001 | S2C-EST - Plug-in base               | S2C-EST       | 1   | piece           |
| 2CSS201997R0013 | S2C-CM1 - Motor operating device     | S2C-CM1       | 1   | piece           |
| 2CSS203997R0013 | S2C-CM2/3 - Motor operating device   | S2C-CM2/3     | 1   | piece           |
| 2CSS204997R0013 | S2C-CM4 - Motor operating device     | S2C-CM4       | 1   | piece           |
| GHS2001901R0003 | S2C-DH - Mechanical Accessories      | S2C-DH        | 1   | piece           |

Where Used (as a spare part for "Products")

| Identifier            | Description              | Qty | Unit Of Measure |
|-----------------------|--------------------------|-----|-----------------|
| 3HAC020536-014        | IRC5 Controller          | 1   | piece           |
| ACS 1000              | No Description Available | 1   | piece           |
| ACS 5000 Water Cooled | No Description Available | 1   | piece           |

Product specific part data

|              |                 | Ron             | ootics Part | Robot Design |
|--------------|-----------------|-----------------|-------------|--------------|
| Product Cate | egory Drive Par | t Category Cate | egory       | Year         |

| Product                  | Category | Drive Part Category             | Robotics Part<br>Category | Robot Design<br>Year |
|--------------------------|----------|---------------------------------|---------------------------|----------------------|
| ACS 1000                 | ACS1000  | Switches, Relays,<br>Contactors |                           |                      |
| ACS 5000 Water<br>Cooled | ACS5000  | Switches, Relays,<br>Contactors |                           |                      |
| 3HAC020536-014           |          |                                 | Drive Module              | IRC5 M2004           |

