


# Transfer Switches




## Single Phase

Fig. A




## Single Phase- Switched Neutral

Fig. B



## Three Phase

Fig. C



## Single Phase 120/240 Volts AC

FIG.	UL	MODEL NUMBER	AMPS		VOLTS	PHASE	WIRE RANGE (CuAl)	CABINET SIZE	HUB* (Included)	UNIT WGT.	STD. PKG.	NEUTRAL KITS (FIELD INSTALLED ONLY) ORDER MODEL #
			MAIN	STANDBY								
A	Y	GS1101B12UL	100	100	120/240	1	10-1/0	2713G	1 1/4"	32	1	NEU102
A	Y	GS3161G	100	100	120/240	1	12-110	1509G	Order Separately	11	1	INSTALLED
A	Y	GS1201B20UL	200	100	120/240	1	6-250	3316G	2"	42	1	NEU202
A	Y	GS1202B20UL	200	200	120/240	1	6-250	3616G	2"	46	1	NEU202
A	Y	GS1402B01UL	400	200	120/240	1	2-600 or (2) 1/0-250	4318G	Order Separately	88	1	NEU407
A	Y	GS1404B01UL	400	400	120/240	1	2-600 or (2) 1/0-250	4318G	Order Separately	96	1	NEU407

## Single Phase 120/240 Volts AC with Attached Meter Socket

FIG.	UL	MODEL NUMBER	AMPS		VOLTS	PHASE	WIRE RANGE (CuAl)	CABINET SIZE	HUB* (Included)	UNIT WGT.	STD. PKG.	NEUTRAL
			MAIN	STANDBY								
A	N	GS1202B20M	200	200	120/240	1	1/0-250	4016M	2"	46	1	INSTALLED

## Single Phase 120/240 Volts AC - Switch Neutral

FIG.	UL	MODEL NUMBER	AMPS		VOLTS	PHASE	WIRE RANGE (CuAl)	CABINET SIZE	HUB* (Included)	UNIT WGT.	STD. PKG.	NEUTRAL KITS (FIELD INSTALLED ONLY) ORDER MODEL #
			MAIN	STANDBY								
B	Y	GS3161B12UL	100	100	120/240	1	10-1/0	2713G	1 1/4"	32	1	Factory Installed
B	Y	GS3262B25UL	200	200	120/240	1	6-250	3616G	2 1/2"	48	1	Factory Installed
B	Y	GS3464B01UL	400	400	120/240	1	2-600 or (2) 1/0-250	4423G	Order Separately	120	1	Factory Installed

## Three Phase 240, 120/208 Volts AC

FIG.	UL	MODEL NUMBER	AMPS		VOLTS	PHASE	WIRE RANGE (CuAl)	CABINET SIZE	HUB* (Included)	UNIT WGT.	STD. PKG.	NEUTRAL KITS (FIELD INSTALLED ONLY) ORDER MODEL #
			MAIN	STANDBY								
C	Y	GS3262G	200	200	240	3	6-250	3016G	Order Separately		1	INSTALLED
C	Y	GS3402B01UL	400	200	240	3	2-600 or (2) 1/0-250	4423G	Order Separately	107	1	NEU404
C	Y	GS3404B01UL	400	400	240	3	2-600 or (2) 1/0-250	4423G	Order Separately	120	1	NEU407

## Three Phase 600 Volt AC

FIG.	UL	MODEL NUMBER	AMPS		VOLTS	PHASE	WIRE RANGE (CuAl)	CABINET SIZE	HUB* (Included)	UNIT WGT.	STD. PKG.	NEUTRAL KITS (FIELD INSTALLED ONLY) ORDER MODEL #
			MAIN	STANDBY								
C	Y	GS3161B12UL	100	100	600	3	10-1/0	2713G	1 1/4"	32	1	NEU102
C	Y	GS3262B25UL	200	200	600	3	6-250	3616G	2 1/2"	48	1	NEU202
C	Y	GS3464B01UL	400	400	600	3	2-600 or (2) 1/0-250	4423G	Order Separately	120	1	NEU407

\* For Hub Model Number see Table on page 96