A-C68 A-BUS® Intermediate System



A-C68 6 Source/8 Zone Multi-zone Controller

Rack mountable, 1-U high, rear RS-232 port, 2 RJ-45 expander jacks, 6 single IR emitters. IR library, sleep timer, IR learning and paging. Controller only, no keypads. Rack ears included.

(42.5 x 26.7 x 5.4 cm) Shipping Weight: 12 lbs (5.4 kg)

16.75"W x 10.5"D x 2.125"H

Dimensions:

2000-527432 A-C68 2000-535062 A-C68-EU/UK





A-C660 6 Source/8 Zone Controller Kit

Includes:

- Multi-zone Controller (A-C68)
- 6 Amplified LCD Keypads (A-K6L)
- System Remote (USRC)
- 6 IR Emitters
- Wall plates not included



Shipping Weight: 18.5 lbs (8.4 kg)

2000-534867 A-C660

2000-534874 A-C660-EU/UK



BTA-2 A-BUS Bluetooth® Module

This wall-mounted local input module integrates with Russound A-BUS multi-room systems. The A-BUS *Bluetooth* receiver streams content to the local A-BUS keypad, so it serves as a local source within any room.







Dimensions: 1.75"W x 2.875"H x 1.75"D (45 x 73 x 45mm)

Shipping Weight: 0.4 lbs (0.18 kg)

2460-536595 BTA-2



BTA-1 A-BUS Bluetooth® Module

Wires in line with CAT-5 between hub or controller and keypad. The A-BUS *Bluetooth* receiver streams content to the local A-BUS keypad. **Works with A-K6L only.**



Dimensions: 2.7"W x 0.9"H x 2.2"D (68 x 23 x 57 mm)

Shipping Weight: 3.1 oz (0.09 kg)

2460-533785 BTA-1



A-K6L

Amplified LCD Keypad

Digital amp, LCD panel and IR receiver. Bass, treble and loudness control. Pre-amp output, configurable turn on and page volume levels. Page enable/disable, RJ-45 connector. Wall plate not included.

CE

Dimensions: 1.75"W x 2.875"H x 1.75"D (45 x 73 x 45mm)
Shipping Weight 0.4 lb (0.18 kg)

2000-534669 A-K6L White



A-K4

Amplified Keypad

Analog amp, IR receiver, preamp outputs, left and right gain controls with RJ-45 connector. Wall plate not included. **See page 48 for color conversion kits.**



Dimensions: 1.75"W \times 2.875"H \times 1.75"D (45 \times 73 \times 45mm) Shipping Weight 0.4 lb (0.18 kg)

2000-534591 A-K4 White



A-LC3

Local Source Input

IR emitter for local source control, auto sensing to override audio, wires in line with CAT-5 between hub or controller and keypad. Wall plate not included. **See page**

CE

plate not included. See page 48 for more colors.

Dimensions: 1.75"W x 2.875"H x 1.75"D (45 x 73 x 45mm)
Shipping Weight 0.4 lb (0.18 kg)
2000-527456 A-LC3 White