



120V INCANDESCENT SINGLE POLE VACANCY SENSOR, MANUAL OPERATION, LIGHT ALMOND

RW500BLACC4 | [Pass & Seymour](#)

FEATURES & BENEFITS

Designed to replace a standard light or fan single pole switch, this vacancy sensor controls most types of lighting and is ideal for bedrooms and baths.



- California Title 24 compliant. .
- Lighted switch for visibility in darkened rooms.
- Manual-ON operation.
- Fixed 30-minute time delay, no adjustment necessary.
- Low-profile styling with uniform color-matched lens and device.
- Coverage: 180 degrees, max. 600 ft.2 (56m2).
- Load: Incandescent.
- For covering patents, see www.legrand.us/patents.

SPECIFICATIONS

GENERAL INFO

Color: Light Almond
Number Of Poles: 1
Number Of Wires: 2

LISTING AGENCIES/THIRD PARTY CERTIFICATIONS

cULus: Yes
UN SPSC: 39121502

DIMENSIONS

Depth (US): 1.88"
Height (US): 2.63"
Width (US): 1.69"

TECHNICAL INFORMATION

Volts (AC): 120VAC, 60Hz
Watts: 25-500W Incandescent

BUY AMERICAN ACT COMPLIANCE

Country Of Origin: CHINA
Buy American Act Status: No