# Eaton FAZ-C32{}2-NA

# Catalog Number: FAZ-C32/2-NA

Eaton FAZ branch protector,UL 489 Industrial miniature circuit breaker - supplementary protector,Medium levels of inrush current are expected,32 A,10 kAIC, 14 kAIC,Two-pole,277/480 V,5-10X /n,50-60 Hz,Screw terminals,C Curve

# General specifications



Eaton FAZ branch protector

EAN

4015081020508

**Product Height** 

4.13 in

**Product Weight** 

1 lb

Certifications

UL 489

CSA Std. C22.2 No. 235

Catalog Number

FAZ-C32/2-NA

Product Length/Depth

1.4 in

**Product Width** 

2.97 in

Warranty

1 year

Catalog Notes

Positioned for medium inrush startup currents to provide protection for small transformers and pilot devices.



Photo is representative



## **Physical Attributes**

Number of poles

Two-pole

**Terminals** 

Screw

Type

UL 489 Industrial miniature circuit breaker - supplementary protector

## Performance Ratings

**Amperage Rating** 

32 A

Circuit protection

C curve

Frequency rating

50-60 Hz

Interrupt rating

14 kAIC

10 kAIC

Trip Type

5-10X /n

Voltage rating

277/480V

#### Miscellaneous

#### Application

Suitable for applications where medium levels of inrush current are expected

#### Resources

#### **Brochures**

Industrial miniature circuit breakers UL 489

#### Catalogs

Eaton's Volume 4—Circuit Protection

Specifications and datasheets

Eaton Specification Sheet - FAZ-C32/2-NA

Product Data Sheet - FAZ-C32/2-NA



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2024 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia