

radiant Collection radiant® Smart LED Dimmer with Wi-Fi, Matter-Enabled, White Part No. WWMRL51WH



Take comfort in the convenience of controlling your lights from any smart device, whether you're home or not. The Smart LED Dimmer with Matter offers precise light level control, and the ability to set scenes and schedules from any Matter-compliant smart home platform. Combining classic design and advanced functionality with a simple connection to your existing smart home solution using your home's existing wireless network, Smart Lighting from the radiant® Collection sets the exact lighting you want – when and where you need it. Works with LED dimmable lamps and loads on typical residential wiring. Does not work with 0-10V LED drivers.

Features & Benefits

is required for successful installation. For a list of Matter controllers, please visit legrand.us/matter

Matter Controller Required: A compatible Matter controller Easy Setup: Simply scan the Matter QR code on the device with your smartphone's camera or smart home application to begin the setup process.

Wi-Fi Connected: Works with a home's existing secure 2.4 GHz Wi-Fi network.

Local Control: Devices are designed to work when your home loses connection to the internet. Devices communicate directly with a Matter controller, allowing for a faster, more reliable local processing of commands without needing an internet connection.

Consolidated Control: Can be controlled through any Matter compliant smart home platform's application - no separate manufacturer application required for onboarding of 2nd Gen Wi-Fi devices

Voice Control: When paired with a voice assistant, use your voice to turn on the lights or set more advance scenes, schedules or routines.

Consistent Look: Mix and match radiant® smart lighting products with standard devices without sacrificing the designer look and feel.

Neutral Wire Required: Switches and dimmers require a neutral wire in the electrical box.

Compatibility: Device comes with Matter built-in, allowing for greater interoperability and compatibility with the latest smart home assistants and platforms - including Apple HomeKit, Google Home, Amazon Alexa and Samsung SmartThings.

Easy Installation: Installs easily in place of an existing switch or dimmer with a neutral wire. Operates in a single-pole or 3-way applications (with use of any 3-way switch).

Load Compatibility: Works with up to 300W Incandescent/Halogen loads and up to 150W LED loads. Screwless Wall Plate Included: Includes a radiant® wall plate in the box.

Specifications

General Info			
Product Line	Pass & Seymour	Color	White
UPC Number	785007449440	Country Of Origin	China

Features	Smart Lighting	Switch Type	Paddle
Number of Switches	1	Works With	Amazon Alexa, Apple Home, Google Home, Matter, Samsung SmartThings
Application Sector	Residential	Standard	ETL
Warranty Type	1-Year Limited Warranty		
Dimensions			
Product Width US	1.72 in	Product Weight US	3.44 lb
Product Depth US	1.4 in	Product Height US	1.8 in
Product Length US	4.2 in		
Listing Agencies /	3rd Party Agencies		
ETL Listed	Yes	FCC Compliant	Yes
ETL Listed Additional Informa		FCC Compliant	Yes
		FCC Compliant	Yes
Additional Informa	tion No	FCC Compliant	Yes
Additional Informa Energy Savings	tion No	FCC Compliant Frequency Rating	Yes 60 Hz
Additional Informa Energy Savings Technical Informat	tion No tion 120V 150W (LED), 120V 300W (Halogen),		
Additional Informa Energy Savings Technical Informat Load Rating	tion No tion 120V 150W (LED), 120V 300W (Halogen), 120V 300W (Incandescent)	Frequency Rating	60 Hz
Additional Informa Energy Savings Technical Informat Load Rating Number of Gangs	tion No tion 120V 150W (LED), 120V 300W (Halogen), 120V 300W (Incandescent)	Frequency Rating Amperage	60 Hz 15 A 3-Way, Single Pole
Additional Informa Energy Savings Technical Informat Load Rating Number of Gangs Bulb Compatibility	tion No tion 120V 150W (LED), 120V 300W (Halogen), 120V 300W (Incandescent) 1 Halogen, Incandescent, LED	Frequency Rating Amperage Number of Poles	60 Hz 15 A 3-Way, Single Pole
Additional Informa Energy Savings Technical Informat Load Rating Number of Gangs Bulb Compatibility Dimming Phase	tion No tion 120V 150W (LED), 120V 300W (Halogen), 120V 300W (Incandescent) 1 Halogen, Incandescent, LED Forward	Frequency Rating Amperage Number of Poles Requires Neutral Wire	60 Hz 15 A 3-Way, Single Pole Yes