



Hardwire Smoke & Carbon Monoxide Talking Alarm

Carbon monoxide is an invisible, odourless, poisonous gas that can be fatal when inhaled. It is the #1 cause of unintentional poisoning deaths in North America.



Features:



• **Ionization Technology** – Better at detecting fast flaming fires.



• **120V AC Direct-Wire** – Interconnects with up to 24 units, of which 18 can be initiating.



• **9V Battery Backup (included)** – Continuous protection in case of power failure.



• **Test / Reset Button** – Tests circuitry and resets alarm.



• **Hush® Button** – Quickly silences nuisance alarms.



• **Talking Alarm** – Voice messages with sounding alarm identify different dangers.

• **2-in-1 unit** – Advanced sensors for detecting both CO and smoke.

900-0119



Specifications:

| | |
|---------------------|--|
| Product dimensions: | 6" x 6" x 1.5" deep |
| Colour / Case Pack: | White / 6 units |
| Electrical Rating: | 120V AC, 60Hz, 60mA, 9V Battery Backup |
| Wiring: | Quick connect plug with 8" pigtails |
| Audio Alarm: | 85dB |
| Temperature Range: | 40°F (4.4°C) to 100°F (37.8°C) |
| Humidity Range: | Up to 85% relative humidity |
| Sensor: | Ionization and Electrochemical |
| Limited Warranty: | 5 Year |
| Weight: | 0.80lb |
| UPC: | 0-47871-00119-4 |

